UHF Antenna Diversity Digital Pilot Ktv Wireless Microphone Series

UHF非真分集、自动选频、数字导频

专业KTV无线麦克风

YTK全新一代ACT系列无线麦克风，坚固耐用的金属外壳，优越性能，智能化、人性化功能让使用更方便，安装更便捷，更宽的频响、更好的动态响应，提供完美无瑕的音质，让使用者畅想于KTV娱乐中。

YTK made a new Generation ACT series wireless microphone,solid and durable metal shell intellectualized and multi-functional function can make a rapid installation , wider frequency response ,better dynamic range, offer a unique sound for KTV application.

- Up to 200 frequencies selectable come with two optional transmitters.
- Use up to 4 simultaneous system-all channels compatible.
- Automatic frequency scanning , automatic transmitter set up.
- Diversity operation for increasing reliability.
- LCD screen shows frequency,antenna active,RF and AF status.

Receiver:

YTKMR-U9320ES

Transmitters | Handheld & Bodypack

- 60MHz selection bandwidth (depending on local frequency plans)
- More than eight hours of operation with a dual AA size battery
- Selectable transmission power for different installation
- LCD screen shows Frequency, transmission power&battery status

ACT-602

- 60MHz selection bandwidth (depending on local frequency plans)
- More than eight hours of operation with a dual AA size battery
- Speaking/singing/Guitar Mode
- LCD screen shows Frequency, battery status

ACT-MRT3

工程配套 Available Matching Set

MR-U9320ES SET A1

- 1接收机+2手持发射器
- 1Receiver+2handheld transmitter



MR-U9320ES SET A2

- 1接收机+2腰包发射器
- 1Receiver+2Bodypack transmitter



MR-U9320ES SET A3

- 1接收机+1手持发射器+1腰包发射器
- 1Receiver+1handheld&1Bodypack transmitter



腰包配套 Bodypack Set

ACT-MRT3 SET L

- 腰包发射器 & 领夹话筒
- Bodypack transmitter & Clip mic



ACT-MRT3 SET H

- 腰包发射器 & 头戴话筒
- Bodypack transmitter & Headset mic



ACT-MRT3 SET G

- 腰包发射器 & 吉他线
- Bodypack transmitter & Guitar cable

MR-U9320ES 接收机

频 段：	UHF650-814MHz
频道总数：	100 组
工作方式:	PLL锁相环回路
动态范围:	>110dB
失真度:	<0.5%
频率响应:	50Hz-18KHz±3db
信噪比：	>90dB
有效使用距离：	>60M
电源供应：	DC14-22V 500mA
音频输出接口：	1*6.3mm 混合输出 &2*XLR平衡输出
接收机原理：	天线分集
产品尺寸：	420*256*49mm

MR-U9320ES Receiver:

Carrier Frequency:	UHF650-814MHz
Channels Total:	100
Oscillation Mode:	PLL Synthesized
Dynamic Range:	>110dB
T.H.D. :	<0.5%
Frequency Response:	50Hz-18KHz±3dB
S/N Ratio:	>90dB
Effective Use Range:	>60M
Power Supply:	DC14-22V 500mA
Audio Output Jack:	1*6.3mm mix output & 2*XLR balance output
Receiver type:	antenna diversity
Product size:	420*256*49mm

ACT-602 手持发射器

发射机功率：	10mW或5mW
工作方式：	PLL锁相环回路
使用电池类型：	2*AA
镜像反应：	>50dB
频率响应：	60Hz-18KHz±3dB
产品尺寸：	Φ55*265mm

ACT-MRT3 腰包发射器

发射机功率：	10mW
工作方式：	PLL锁相环回路
使用电池类型：	2*AA
镜像反应：	>50dB
频率响应：	50Hz-18KHz±3dB
产品尺寸：	63*22*106mm

ACT-602 Handheld Transmitter:

Transmission Power:	10mW or 5mW
Modulation Mode:	PLL Synthesized
Battery type:	2*AA
Image and Spurious Rejection:	>50dB
Frequency Response:	60Hz-18KHz±3dB
Product size:	Φ55*265mm

ACT-MRT3 Bodypack Transmitter:

Transmission Power:	10mW
Modulation Mode:	PLL Synthesized
Battery type:	2*AA
Image and Spurious Rejection:	>50dB
Frequency Response:	50Hz-18KHz±3dB
Product size:	63*22*106mm